

# CHP Max Headend Optics Platform

CHP-R4RRXF-30-L, CHP-4RRXF-30-L  
Redundant/Non-Redundant  
Quad Return Path Receiver

## FEATURES

- Expand subscriber upstream capacity without increasing headend footprint
- Optimize headend and hub efficiencies with industry leading density and low power consumption
- 300 MHz bandwidth supporting DOCSIS® 3.1 upgrades
- Improve system uptime with automatic failover option
- Configure, monitor, and manage with CORView™ Element Management System
- Automatic Gain Control feature to allow for better level control with redundancy



## PRODUCT OVERVIEW

The CHP Quad Return Path Receiver is an integral part of a flexible return path system. Designed to operate as either a stand-alone or redundant module, the CHP Quad Receiver allows operators to increase their network capacity while reducing operational power. With support for up to 300 MHz of return bandwidth, the CHP Quad Receiver is an ideal choice for supporting future DOCSIS 3.1 band splits without out having to upgrade receivers.



The CHP Quad Return Path Receiver accepts four optical inputs into a single-wide module, which supports up to 40 receivers in a single 2RU CHP chassis and up to 800 receivers in a standard 40RU rack. As operators add bandwidth to their networks, the CHP Quad Receiver can help them to achieve industry leading density.

The CHP Quad Receiver is available in both redundant and non-redundant configurations. The redundant model protects both the optical path and vital hardware for VoIP, business data services, and other critical applications. For additional protection, the redundant model’s integral optical and RF switches alternate between diverse paths when the receiver detects an optical path module hardware fault. In these instances, switch time is less than 50 milliseconds. Operators can pair redundant and non-redundant modules in either the same CHP chassis or in a spare chassis up to 6 meters away.

The CHP Quad Receiver offers high RF output with excellent power efficiency, typically consuming less than 3 Watts per RF channel. The modules are hot-swappable to ensure minimal loss of uptime. The receiver’s Craft Graphical User Interface (GUI) provides local monitoring, configuration control, and firmware downloads, while the System Management Module (SMM) provides local and remote IP access to the Craft GUI, firmware downloads, and the SNMP HMS interface.

Automatic Gain Control allows for user to set the RF output level and have a window of optical input range to maintain the set output.

**OPTIONS**

Redundant or Non-Redundant

CORView™ Element Management System

**GENERAL SPECIFICATIONS**

	CHP-R4RRXF-30-L	CHP-4RRXF-30-L
<b>Optical Specifications</b>		
Input Wavelength Range	1260 to 1620 nm	1260 to 1620 nm
Optical Input Range	-20 to 3 dBm	-20 to 3 dBm
Optical Return Loss	55 dB	55 dB
<b>RF Specifications</b>		
RF Output Bandwidth	5 to 300 MHz	5 to 300 MHz
RF Output Level, min. per channel (Note 1)	40 dBmV	40 dBmV
Flatness, peak-to-valley	± 0.75 dB with respect to gain slope	± 0.75 dB with respect to gain slope
Gain Slope	± 1.0 dB	± 1.0 dB
RF Gain Adjustment Range (Note 2)	0 to -31.5 in 0.5 dB steps	0 to -31.5 in 0.5 dB steps
RF Output Return Loss, min.	16 dB	16 dB
RF Testpoint	-20 ± 0.5 dB	-20 ± 0.5 dB
<b>Performance Specifications</b>		
Equivalent Input Noise	< 4.5 pA/Hz <sup>0.5</sup>	< 4.5 pA/Hz <sup>0.5</sup>
Maximum Peak NPR Variation	4 dB	4 dB
Noise-to-Power Ratio (NPR)/Dynamic Range	40/13 dB	40/13 dB
BER Dynamic Range	> 40 dB	> 40 dB
Optical Input to RF Output Terminated Isolation	≥ 60 dB	≥ 60 dB
Channel-to-Channel Isolation	5 to 300 MHz @60 dB	5 to 300 MHz @60 dB
Redundant Switching Time	50 ms	N/A
Power Consumption	12 W	12 W
<b>Mechanical Specifications</b>		
Dimensions (W x H x D) in (cm)	1.25 x 3.44 x 18.5 in (3.18 x 8.74 x 46.99 cm)	1.25 x 3.44 x 18.5 in (3.18 x 8.74 x 46.99 cm)
<b>Environmental Specifications</b>		
Operating Temperature Range	0° to 50°C (32° to 122°F)	0° to 50°C (32° to 122°F)
Operating Humidity, Non-condensing	10 to 90%	10 to 90%

**NOTES:**

- 1. RF output is based on -9 dBm optical input at 7% OMI.
- 2. The attenuator for each channel in the modules may be adjusted in 0.5dB steps from 0 to 31.5 dB.

**RELATED PRODUCTS**

CHP Chassis	Optical Patch Cords
Power Supplies	Optical Passives
Management Module	Installation Services

## Customer Care

Contact Customer Care for product information and sales:

- United States: 866-36-ARRIS
- International: +1-678-473-5656

**Note:** Specifications are subject to change without notice.

**Copyright Statement:** ©ARRIS Enterprises, LLC, 2018. All rights reserved. No part of this publication may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation, or adaptation) without written permission from ARRIS Enterprises, LLC ("ARRIS"). ARRIS reserves the right to revise this publication and to make changes in content from time to time without obligation on the part of ARRIS to provide notification of such revision or change. ARRIS and the ARRIS logo are registered trademarks of ARRIS Enterprises, LLC. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks or the names of their products. ARRIS disclaims proprietary interest in the marks and names of others. The capabilities, system requirements and/or compatibility with third-party products described herein are subject to change without notice.